

MAGNETIC SENSOR AND MANUFACTURING METHOD THEREFOR

CROSS REFERENCE TO RELATED APPLICATIONS

This application is based on and incorporates herein
5 by reference Japanese Patent Applications No. 2001-63524 filed
on March 7, 2001 and No. 2002-32565, filed on February 8, 2002.

FIELD OF THE INVENTION

The present invention relates to a magnetic sensor
10 using magnetic tunnel junction devices as magnetoresistive
devices and a manufacturing method therefor.

BACKGROUND OF THE INVENTION

In a magnetic sensor, as shown in Fig. 1B, two
15 magnetoresistive devices R_1 and R_2 are connected in series on
a substrate 10. Each of the magnetoresistive devices R_1 and R_2
is constructed with one or a series of two or more magnetic tunnel
junction devices (TMR devices) and one of the magnetoresistive
devices (for example, R_2) is magnetically shielded.

20 In this magnetic sensor, the temperature
characteristics of the magnetoresistive devices R_1 and R_2 are
virtually identical. Therefore, when a given voltage is applied
between electric terminals Pa and Pb at one end and the other
of the serial path of the magnetoresistive devices R_1 and R_2 and
25 no external magnetic field is applied into the plane of the
substrate 10, a constant output voltage is produced between the
electric terminals Pc and Pb (or Pa and Pc) at both ends of the

magnetoresistive device R_2 (or R_1) regardless of the temperature. The constant output voltage is, for example, $V_{in}/2$, where V_{in} represents the voltage between the terminals Pa and Pb.

5 When an external magnetic field is applied to the plane of the substrate 10, the electric resistance of the magnetoresistive device R_1 varies depending on the orientation and magnitude of the magnetic field. Thus the output voltage between the terminals Pc and Pb (or Pa and Pc) varies as the electric resistance changes. In the TMR devices which constitute the magnetoresistive devices R_1 and R_2 , the change in resistance is very small even when the ambient temperature varies with an external magnetic field. Consequently, this magnetic sensor shows a favorable temperature characteristic.

10 However, in the manufacturing process, when fixing the chip to a lead frame, the chip is likely to crack at the portion covered by a magnetic shield layer 42 due to changes of temperature from a heat treatment temperature level to a room temperature level.

20 SUMMARY OF THE INVENTION

It is an object of the present invention to provide a magnetic sensor which is least likely to cause cracking and a manufacturing method therefor.

25 According to the present invention, magnetoresistive devices are formed on the insulating surface of a substrate. The devices are connected in series through an insulating film using a wiring layer formed on the surface of the substrate.

An insulating film for passivation is formed to cover the devices and the wiring layer. A magnetic shield layer is formed on the passivation insulating film through an organic film for relieving thermal stress to cover one of the devices. After removal of the sensor chip containing the magnetoresistive devices and other components from the wafer, the chip is bonded to a lead frame through an Ag paste layer by heat treatment. Preferably, the magnetic shield layer is made of a Ni-Fe alloy having a Ni content of 69% or less.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects, features and advantages of the present invention will become more apparent from the following detailed description made with reference to the accompanying drawings: In the drawings:

Fig. 1A is a sectional view showing a magnetic sensor according to a first embodiment of the present invention, and Fig. 1B is an equivalent circuit diagram of the magnetic sensor;

Fig. 2A is a sectional view showing a step of forming groups of TMR devices of the magnetic sensor, Fig. 2B is a sectional view showing a step of forming wire connections of the magnetic sensor, and Fig. 2C is a sectional view showing a step of forming an insulating film of the magnetic sensor;

Fig. 3A is a sectional view showing a step of forming an organic film for the magnetic sensor, and Fig. 3B is a sectional view showing a step of forming a shield layer and the step of forming a resist layer of the magnetic sensor;

Fig. 4A is a sectional view showing a step of selective coating with a Ni-Fe alloy of the magnetic sensor, and Fig. 4B is a sectional view showing a step of removing the resist layer and a step of selectively removing the shield layer of the magnetic sensor;

Fig. 5 is a sectional view showing a step of forming an organic film which follows the steps shown in Fig. 4B;

Fig. 6 is a sectional view showing a step of selectively etching an insulating film for passivation which follows the step shown in Fig. 5;

Fig. 7 is a top view showing the groups of TMR devices shown in Fig. 2A;

Fig. 8 is a sectional view taken along the line VIII-VIII in Fig. 7 showing the film forming step in the TMR device pair forming process;

Fig. 9 is a sectional view showing a step of ion milling which follows the step shown in Fig. 8;

Fig. 10 is a sectional view showing a step of ion milling which follows the step shown in Fig. 9;

Fig. 11 is a top view showing the magnetic sensor shown in Fig. 2B;

Fig. 12A is a top view showing the layout of TMR device pairs, Fig. 12B is a top view showing an example of a magnetic sensor using the groups of TMR devices shown in Fig. 12A, and Fig. 12C is a top view showing another example of a magnetic sensor using the groups of TMR devices shown in Fig. 12A;

Fig. 13 is a top view showing the organic film shown

in Fig. 3A;

Fig. 14 is a top view showing the resist layer shown in Fig. 3B;

Fig. 15 is a top view showing the resist layer and magnetic shield layer shown in Fig. 4A;

Fig. 16 is a top view showing the organic film and magnetic shield layer shown in Fig. 4B;

Fig. 17 is a top view showing the organic film covering the magnetic shield layer shown in Fig. 5;

Fig. 18 is a sectional view showing a magnetic sensor chip fixed onto a lead frame;

Fig. 19 is a sectional view showing a magnetic sensor chip connected with a bonding wire;

Fig. 20 is an equivalent circuit diagram showing a magnetic sensor according to a second embodiment of the present invention;

Fig. 21 is a top view showing an analytic model based on computer simulation;

Fig. 22 is a sectional view taken along the line T-T' of Fig. 21 showing a thermal stress relief film in a fixed magnetic shield layer structure;

Fig. 23 is a graph showing the relation between the thickness of the thermal stress relief film and the maximum stress generated on the surface of the silicon chip surface;

Fig. 24 is a sectional view taken along the line XXIV-XXIV in Fig. 21 showing a magnetic shield layer of Ni-Fe alloy in a magnetic shield layer structure;

Fig. 25 is a graph showing the relation between the Ni content of Ni-Fe alloy and the maximum stress generated on the surface of the silicon chip surface;

Fig. 26 is a graph showing the maximum stress generated on the surface of the silicon chip surface concerning a Ni-Fe alloy with a Ni content of 81% and one with a Ni content of 45%;

Fig. 27 is a sectional view taken along the line XXVII-XXVII in Fig. 21 showing a magnetic shield layer structure which has no undercut at the bottom of each side wall of the magnetic shield layer;

Fig. 28 is a sectional view taken along the line XXVIII-XXVIII in Fig. 21 showing a magnetic shield layer structure which has an undercut with a square cross section at the bottom of each side wall of the magnetic shield layer;

Fig. 29 is a sectional view taken along the line IXXX-IXXX in Fig. 21 showing a magnetic shield layer structure which has an undercut with a triangular cross section at the bottom of each side wall of the magnetic shield layer; and

Fig. 30 is a graph showing the maximum stress generated on the surface of the silicon chip surface concerning the magnetic shield layer structures shown in Figs. 27 to 29.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

(First Embodiment)

Referring first to Fig. 1A, a magnetic sensor according to the first embodiment has magnetoresistive devices

5 R_1 and R_2 arranged in series on the insulating surface of a substrate 10 as illustrated in Fig. 1B. Each of the magnetoresistive devices is constructed with a plurality of TMR devices arranged in series. T_1 to T_6 represent TMR device pairs each of which is constructed with a pair of TMR devices connected in series through a lower electrode layer 12 as typically observed in T_1 . The device pairs T_1 to T_6 are virtually identical in structure and the method for forming the TMR devices will be described later. It is also possible that each magnetoresistive device R_1 or R_2 comprises a single TMR device.

10
15
20
25
An interlayer insulating film 30 of silicon oxide or a similar material is formed on the surface of the substrate 10, covering the TMR device pairs T_1 to T_6 . Also, a wiring layer 32 including Al layers W_a to W_c and W_1 to W_4 is formed on the insulating film 30. The Al layer W_a is led out from one TMR device of the device pair T_1 . A part of the Al layer W_a constitutes an electric terminal or bonding pad P_a shown in Fig. 1B. The Al layer W_1 interconnects the other TMR device of the pair T_1 and one TMR device of the pair T_2 , and the Al layer W_2 interconnects the other TMR device of the pair T_2 and one TMR device of the pair T_3 . The Al layer W_c is led out from the other TMR device of the device pair T_3 . A part of the Al layer W_c constitutes an electric terminal or bonding pad P_c shown in Fig. 1B. In this way, the magnetoresistive device R_1 between bonding pads P_a and P_c is constructed with TMR device pairs T_1 to T_3 connected in series.

The Al layer W_c interconnects the other TMR device

of the device pair T_3 , and one TMR device of the device pair T_4 . The Al layer W_3 interconnects the other TMR device of the device pair T_4 and one TMR device of the device pair T_5 . The Al layer W_4 interconnects the other TMR device of the device pair T_5 and one TMR device of the device pair T_6 . The Al layer W_b is led out from the other TMR device of the device pair T_6 . A part of the Al layer W_b constitutes an electric terminal or bonding pad P_b shown in Fig. 1B. In this way, the magnetoresistive device R_2 between bonding pads P_c and P_b is constructed with TMR device pairs T_4 to T_6 connected in series. Bonding pad P_c is led out from the portion of interconnection of the magnetoresistive devices R_1 and R_2 .

On the surface of the substrate 10, an insulating film 34 is provided for passivation covering the insulating film 30 and wiring layer 32. The insulating film 34 is, for example, a silicon oxide film, silicon nitride film or a lamination of these films. The insulating film 34 has connecting holes 34a, 34b and 34c which expose the bonding pads of the wiring layers W_a , W_b and W_c .

On the insulating film 34, an organic film 36 is provided for relieving thermal stress. The organic film 36 is, for example, a polyimide film, resist film or benzocyclobutene film. It has, for example, a thickness of 0.5-1.0 μm or so. It has connecting holes 36a, 36b and 36c, which are continuous with the connecting holes 34a, 34b, 34c of the insulating film 34, respectively.

On the organic film 36, a magnetic shield layer 42

is provided to cover the magnetoresistive device R_2 through the organic film 36 and the insulating film 34. The magnetic shield layer 42 is made of a high-permeability magnetic material such as Ni-Fe alloy.

5 On the organic film 36, an organic film 44 is provided to cover the magnetic shield layer 42. The organic film 44 is, for example, a polyimide film, resist film or benzocyclobutene film. Usually, its thickness is equal to or larger than the thickness of the magnetic shield film 42, for example, 10 μm .
10 The organic film 44 has connecting holes 44a, 44b and 44c, which are continuous with the connecting holes 36a, 36b, 36c of the insulating film 36, respectively.

15 In this embodiment, each of the connecting holes 34a to 34c is a square of 100 $\mu\text{m} \times 100 \mu\text{m}$; the connecting holes 36a to 36c are slightly larger than the connecting holes 34a to 34c; and the connecting holes 44a to 44c are slightly larger than the connecting holes 34a to 34c. Therefore, the connecting
20 holes for the respective bonding pads are somewhat fan-shaped with a gradual outward increase in size, which facilitates bonding of wires of Au or a similar material to the bonding pads. It is desirable to use an electrically insulating material for the organic films 36 and 34 in order to prevent shorting of wires during wire bonding work.

25 The substrate (magnetic sensor chip) 10 shown in Fig. 1A is separated from the wafer by dicing. The other main surface (reverse) of the chip, or the surface reverse to the surface where the magnetoresistive devices R_1 and R_2 , the magnetic shield

layer 42 and so on are formed, is fixed to a Cu lead frame through an Ag paste layer by heat treatment. While the temperature is decreasing from a heat treatment temperature level to a room temperature level, the organic film 36 relieves thermal stress caused by the difference in the thermal expansion coefficient between the chip and the magnetic shield layer 42, which prevents cracking in the chip at its portion covered by the magnetic shield layer 42.

After the above wire bonding following the step of fixing the chip to the lead frame, the chip, the chip support of the lead frame and bonding wires may be housed in a plastic package by a resin molding process. If the filler in the resin and the magnetic shield layer repeatedly expand and contract due to temperature changes during the resin molding process or a subsequent process, the magnetic shield layer 42 may peel off the organic film 36. Such peeling can be prevented by the organic film 44.

Next, a method for manufacturing the magnetic sensor will be described with reference to Figs. 2A-2C to Fig. 19.

First as shown in Fig. 2A, a TMR device group T_{11} including TMR device pairs T_1 to T_3 and a TMR device group T_{21} including TMR device pairs T_4 to T_6 are formed on the surface of the substrate 10. The TMR device group pattern may be like the one shown in Fig. 7. In this pattern, the same TMR device groups T_{12} to T_{15} as the TMR device group T_{11} are arranged in line with T_{11} and the same TMR device groups T_{22} to T_{25} as the TMR device group T_{21} are arranged in line with T_{21} . This pattern may be

changed as shown in Fig. 12A which includes only the device groups T_{11} and T_{21} .

In the device groups T_{11} to T_{15} and T_{21} to T_{25} , their TMR device pairs are virtually identical in structure, so as a typical example, a method for manufacturing the TMR device pair T_1 will be explained referring to Figs. 8 to 10.

At step shown in Fig. 8, the insulating substrate 10 is prepared by forming a silicon oxide film 10b on the surface of a silicon substrate 10a by thermal oxidation. The substrate 10 may be an insulating substrate made of glass, quartz or the like. A 10-30 nm thick Cr layer as the electrode material layer 12 is formed on the insulating surface of the substrate 10 by sputtering. The electrode material layer 12 may be a single Ti layer or a lamination of a Ti layer and a Cu layer, or an insulating nonmagnetic metal material such as W, Ta, Au or Mo may be used.

Next, a 30-50 nm thick layer of Pt-Mn alloy 14 is formed as an anti-ferromagnetic layer on the layer 12 by sputtering. The material for the anti-ferromagnetic layer may be a Rh-Mn alloy, Fe-Mn alloy or the like. Then, a 10 nm thick Ni-Fe alloy layer 16 is formed as a ferromagnetic layer on the Pt-Mn alloy layer 14 by sputtering. The material for this ferromagnetic layer may be Ni, Fe or Co or an alloy of two or more metals among Ni, Fe and Co or an intermetallic compound. A multilayered structure such as a lamination of an upper Ni-Fe alloy layer and a lower Co layer may be used as well.

Then, a 1-2 nm thick Al layer is formed on the Ni-Fe alloy layer 16 by sputtering. An alumina (AlO_x) layer 18 is

formed by oxidizing the Al layer. The alumina layer 18 is used as a tunnel barrier layer. For the tunnel barrier layer, an oxide as a modified form of metal or semiconductor (e.g., TiO_x , SiO_2 , MgO , $\text{Al}_2\text{O}_3+\text{SiO}_2$ [SIALON]) or a nitride (e.g., AlN , Si_3N_4), or an oxide nitride (e.g., $\text{AlN}+\text{Al}_2\text{O}_3$) may be used.

Next, a 20-100 nm thick Ni-Fe alloy layer 20 is formed as a ferromagnetic layer on the alumina layer 18 by sputtering. Instead of this ferromagnetic layer 20, a ferromagnetic layer similar to the one used for the layer 16 may be used. Then, a 30-60 nm thick Mo layer 22 is formed on the Ni-Fe alloy layer 20 by sputtering. The Mo layer 22 is used to form an upper electrode layer, and it also serves as an etching stopper at the step of forming connecting holes for the Al layer (Wa, etc. in Fig. 1A) in the insulating film 30 by etching.

At step shown in Fig. 9, the lamination ranging from the Cr layer 12 to the Mo layer 22 is patterned by ion milling using a resist layer as a mask in accordance with a predetermined lower electrode pattern. Then the resist layer used for this patterning is removed.

At step shown in Fig. 10, the lamination ranging from the Pt-Mn alloy layer 14 to the Mo layer 22 is patterned by ion milling using a resist layer as a mask in accordance with two predetermined upper electrode patterns. Then the resist layer used for this patterning is removed. As a consequence, the first TMR device Ta and the second TMR device Tb are produced. The first TMR device Ta is a lamination constituted of the Cr layer 12, Pt-Mn alloy layer 14a, Ni-Fe alloy layer 16a, alumina layer

18a, Ni-Fe alloy layer 20a and Mo layer 22a. The second TMR device Tb is a lamination constituted of the Cr layer 12, Pt-Mn alloy layer 14b, Ni-Fe alloy layer 16b, alumina layer 18b, Ni-Fe alloy layer 20b and Mo layer 22b. These devices Ta and Tb are connected in series by the lower electrode layer (Cr layer) 12 to constitute the TMR device pair T_1 .

In the TMR device pair T_1 shown in Fig. 10, the Pt-Mn alloy layers 14a and 14b function to fix the orientation of magnetization in the Ni-Fe alloy layers 16a and 16b, respectively. As a result, the Ni-Fe alloy layers 16a and 16b are both fixed magnetization layers. On the other hand, the orientation of magnetization in the Ni-Fe alloy layers 20a and 20b is free, and they are free magnetization layers.

When an external magnetic field is applied to the plane of the substrate 10 while a given current is flowing through the space between the upper electrode (Mo) layers 22a and 22b, the relative angle in magnetization between the ferromagnetic layers (between the Ni-Fe alloy layers 16a and 20a, and between the Ni-Fe alloy layers 16b and 20b) varies depending on the orientation and magnitude of magnetization, and the electric resistance between the upper electrode layers 22a and 22b varies with the changes in the relative angle. The resistance is minimum when the orientations of magnetization of the two layers are parallel to each other, while the resistance is maximum when they are antiparallel. Accordingly, the magnetic field can be detected through the resistance changes.

In the TMR device pair T_1 shown in Fig. 10, it is also

possible that the Pt-Mn alloy layers 14a and 14b lie over the Ni-Fe alloy layers 20a and 20b, respectively. The Ni-Fe alloy layers 20a and 20b are both fixed magnetization layers while the Ni-Fe alloy layers 16a and 16b are free magnetization layers.

5 At step shown in Fig. 2B, the interlayer insulating film 30 which covers the TMR device groups such as T_{11} and T_{21} is formed over the surface of the substrate 10. For example, a silicon oxide layer is formed as the insulating film 30 by sputtering. Connecting holes necessary for wiring are formed in the insulating film 30 by ion milling using a resist layer as a mask. Then, an Al layer is formed on the insulating film 30 by sputtering and the Al layer is patterned by wet etching using a resist layer as a mask to form the wiring layer 32, which includes the remaining Al layer portions W_a to W_c and W_1 to W_4 .

10
15
20
25 If the TMR device group pattern shown in Fig. 7 is adopted, the pattern shown in Fig. 11 can be used as a wiring pattern. In the case of the pattern shown in Fig. 11, connections of the TMR device pairs T_1 to T_3 (TMR device group T_{11}) and TMR device pairs T_4 to T_6 (TMR device group T_{21}) by the Al layers W_1 , W_2 , W_c , W_3 and W_4 are made in the same manner as described by reference to Fig. 1. TMR device groups T_{12} to T_{15} are connected in series between the Al layer W_a integral with the bonding pad P_a , and the TMR device group T_{11} . TMR device groups T_{22} to T_{25} are connected in series between the Al layer W_b integral with the bonding pad P_b , and the TMR device group T_{21} . Here, W_{11} to W_{22} represent Al layers used for serial connection of TMR device groups T_{11} to T_{15} and W_{31} to W_{42} represent Al layers used for serial

connection of TMR device groups T_{21} to T_{26} .

The magnetoresistive device R_1 is constructed with serially connected TMR device groups T_{11} to T_{15} , while the magnetoresistive device R_2 is constructed with serially connected TMR device groups T_{21} to T_{25} . As an extension of the space between the TMR device groups T_{12} to T_{15} and the TMR device groups T_{22} to T_{25} , part of the Al layer Wc constitutes a bonding pad Pc which is in line with bonding pads Pa and Pb. For brevity, Fig. 2B shows the cross sections taken along the lines J-J', K-K', L-L', M-M' and N-N' of Fig. 11 in connected form.

If the TMR device group pattern shown in Fig. 12A is adopted, the pattern shown in Fig. 12B or 12C can be used as a wiring pattern. As illustrated in Fig. 12B or 12C, the magnetoresistive device R_1 is constructed with TMR device pair T_1 to T_3 (TMR device group T_{11}) while the magnetoresistive device R_2 is constructed with TMR device pairs T_4 to T_6 (TMR device group T_{21}). Connections of the TMR device pairs T_1 to T_6 by the Al layers Wa to Wc and W_1 to W_4 are made as described above by reference to Fig. 1A. The cross section shown in Fig. 2B corresponds to a cross section taken along the line IIB-IIB in Fig. 12B and also one taken along the line IIB-IIB in Fig. 12C.

At step shown in Fig. 2C, the insulating film 34 for passivation which covers the wiring layer 32 is formed over the insulating film 30. Preferably a film with high density texture should be used for passivation. One example of the method for forming this film is as follows: a 150 nm thick silicon oxide film is first formed using the plasma CVD method, followed by

formation of a 1000 nm thick silicon nitride film. The characteristics of TMR devices deteriorate at 300°C or more. To avoid such deterioration, 250°C is used as a film forming temperature in the plasma CVD method.

5 At step shown in Fig. 3A, the organic film 36 for relief of thermal stress is formed on the insulating film 34. Explanations given in association with the step of Fig. 3A and subsequent steps assume that the TMR device group pattern shown in Fig. 7 is adopted. Covering the magnetoresistive devices R_1 and R_2 and bonding pads Pa to Pc, the organic film 36 forms a plane pattern shown in Fig. 13.

10
15
20
25
As a typical process of preparing the organic film 36, a 0.5-1 μm thick polyimide film is formed. Specifically, polyimide is coated on the upper face of the substrate by a spin coater, and then the coating is pre-baked on a hot plate at 50°C for 30 minutes and then at 125°C for 3 minutes. Then a positive resist layer is formed on the pre-baked polyimide film by rotary coating or a similar method. This positive resist layer is subjected to exposure and development to form three holes corresponding to the connecting holes 36a to 36c. As a result of this development process, three holes are formed in the positive resist layer and the polyimide film is etched by the developing solution with the positive resist layer as a mask so that the connecting holes 36a to 36c are formed in the polyimide film as the organic film 36 as shown in Figs. 3A and 13.

After removal of the positive resist layer, the

polyimide layer is set by 1-hour heat treatment at 250°C to become a film suitable for practical use. In order to avoid such deterioration in TMR device characteristics as described above concerning the plasma CVD process, it is desirable to use a heat treatment temperature of below 300°C. Since the reaction of the polyimide itself is completed at 200°C or less and the boiling point of the solvent is not more than 210°C, it can be set to an intended degree as far as the heat treatment temperature is 200°C or more. If a resist film is used as the organic film 36, it may be heat-treated, for example, at 250°C for one hour. If a benzocyclobutene film is used as the organic film 36, it may be heat-treated, for example, at 230°C for one hour.

At step shown in Fig. 3B, a seed layer for selective coating which covers the organic film 36 and connecting holes 36a to 36c is formed. A typical process of forming the seed layer 38 is as follows: a lamination layer is formed by laying a 200 nm thick Ni-Fe alloy layer over a 20 nm thick Cr layer by sputtering, then a resist layer 40 is formed on the seed layer 38 to form a plane pattern as illustrated in Fig. 14, where the resist layer should have a hole 40a to expose the part of the seed layer 38 to be coated (which corresponds to the magnetic shield layer 42). The thickness of the resist layer 40 may be, for example, 3 μm .

At step shown in Fig. 4A, the magnetic shield layer 42 is formed by selective coating with the resist layer 40 as a mask, to form a plane pattern as illustrated in Fig. 15. A typical method of forming the magnetic shield layer 42 is that

a 10 μm thick magnetic layer of Ni-Fe alloy is formed by electrolytic coating. Here, the coating conditions are as follows.

Coating liquid: mixture of nickel sulfate, iron sulfate,
boric acid, ammonium chloride, sodium dodecyl sulfate,
saccharin sodium and ascorbic acid

Temperature: fixed temperature between 45°C and 60°C

Current density: 3.5 A/dm²

The thicker the magnetic shield layer 42 is, the larger the shielding effect of is. Therefore, the thickness should be determined depending on the required level of shielding effect. If the magnetic shield layer is thick, the portion of the layer which is above the resist layer may protrude horizontally. To prevent such protrusion, the viscosity of the resist layer 40 should be increased and its thickness should be at least 10 μm .

At step shown in Fig. 4B, after the resist layer 40 is removed using a resist removing agent such as acetone, portions of the seed layer 38, which are not covered by the magnetic shield layer 42 are removed by ion milling. This removal work may be done by wet etching instead of by ion milling. As a result of the removal step shown in Fig. 4B, the magnetic shield layer 42 remains on the organic film 36 through the remaining portion of the seed layer 38, a plane pattern is formed as illustrated in Fig. 16.

At step shown in Fig. 5, an organic film 44 which covers the magnetic shield layer 42 is formed on the organic film 36

to form a plane pattern as illustrated in Fig. 17. As a typical process of preparing the organic film 44, a 10 μm thick polyimide film is formed in the same manner as described above for the organic film 36. In addition, the connecting holes 44a to 44c as continuous with connecting holes 36a to 36c are formed in the organic film (polyimide film) 44 by etching with the same developing solution as used for development of the positive resist layer formed on the polyimide film, as illustrated in Figs. 5 and 17.

At step shown in Fig. 6, the connecting holes 34a to 34c as the respective continuous with connecting holes 36a to 36c are formed in the insulating film 34 by selective etching with the organic films 36 and 44 as masks. For the selective etching process, the responsive ion etching (RIE) technique is employed. The etching conditions which may be used are given below as an example:

Etching gas: CF_4

Pressure: 0.05 Torr

RF power: 240 W/ 200 mm ϕ

According to the above magnetic sensor manufacturing method, the connecting holes 36a to 36c are formed before setting of the organic film 36. Therefore, the etching work for forming the connecting holes is easy. In the process from the step of Fig. 3A to the step of Fig. 5, the magnetoresistive devices R_1 and R_2 , wiring layer 32 and bonding pads Pa to Pc are protected by the insulating film 34, so the magnetoresistive devices R_1 and R_2 , wiring layer 32 and bonding pads Pa to Pc are not damaged

while the organic films 36 and 44, and the magnetic shield layer 42 are being formed. This implies an improvement in yield rate.

After the step shown in Fig. 6, the magnetic sensor chip as shown in Fig. 6 is separated from the silicon wafer by dicing. The other main surface (reverse) of the chip, or the surface reverse to the surface where the magnetoresistive devices R_1 and R_2 , the magnetic shield layer 42 and so on are formed, is fixed to a Cu lead frame 50 through an Ag paste layer 52 by heat treatment, as illustrated in Fig. 18. For setting of the Ag paste layer 52, heat treatment is performed at 150°C for 90 minutes or at 180°C for 60 minutes depending on the type of Ag paste used.

If, in the magnetic sensor chip shown in Fig. 6, the magnetic shield layer 42 should be formed on the insulating film 34 in the absence of the organic film 36, cracking might occur in the chip at the portion covered by the magnetic shield 42 while the temperature is decreasing from the heat treatment temperature level to a room temperature level. The following is the analysis about the mechanism in which such cracking occurs. Table 1 below shows expansion coefficients of various materials.

[Table 1]

Material	Coefficient of expansion (/°C)
Si	$2.6-3.6 \times 10^{-6}$
Ni ₈₁ Fe ₁₉	$12-13 \times 10^{-6}$
Cu	17×10^{-6}
Fe alloy (42 alloy)	$4.4-7.0 \times 10^{-6}$
Au	23×10^{-6}

These materials are used as follows. Silicon (Si) is a material for the substrate of the chip; Ni-Fe alloy (Ni₈₁Fe₁₉)

is a material for the magnetic shield layer 42; and copper (Cu) is a material for the lead frame 50. The expansion coefficient of Fe alloy (42 alloy) is given here for the purpose of comparison and gold (Au) is a material for the substitute film used instead of the organic film 36 as stated later.

Cu as a material for the lead frame 50 has an expansion coefficient larger than that of Fe alloy (42 alloy), a common lead frame material, and the silicon used for the substrate. For this reason, stress is produced between the lead frame 50 and the silicon substrate of the chip during cooling after Ag paste heat treatment. If other conditions are poor, cracking might occur just because of this stress. When a magnetic shield layer 42 made of $\text{Ni}_{81}\text{Fe}_{19}$, which has an expansion coefficient larger than that of silicon, is formed on the silicon substrate, stress occurs between the magnetic shield layer 42 and the silicon substrate, increasing the possibility of cracking. Factors which relate to cracking may include: (a) size, thickness and shape of the silicon substrate; (b) size, thickness and shape of the magnetic shield layer 42; and (c) Ag paste heat treatment temperature.

In the embodiment, for relief of thermal stress due to the above difference in expansion coefficients, the flexible organic film 36 lies between the insulating film 34 for passivation and magnetic shield layer 42 which cover the silicon substrate.

In order to confirm the effect, ~~different samples~~
(~~magnetic sensor chips~~) on which different types of films are

Sub
A1
conc.

formed for the organic film 36 were prepared and experiments were conducted to investigate how cracking would occur. Specifically, for the organic film 36, three samples with different types of films as listed in Table 2, that is, a 0.5 μm thick polyimide film, a 1 μm thick polyimide film and a 0.7 μm thick resist film, were prepared. The chip was fixed to the Cu lead frame 50 through the Ag paste layer 52 by heat treatment (180°C, 60 min), followed by the step of cooling down to a room temperature and further down to -140°C to measure the temperature at which cracking began to occur. The measurement results are shown in Table 2 as "Cracking temperature."

[Table 2]

Organic film	Material	Polyimide	Polyimide	Resist
	Thickness	0.5 μm	1 μm	0.7 μm
Cracking temperature		-40 °C or less	-40 °C or less	-40 °C or less

Among the three samples, the two samples which use a polyimide film as the organic film 36 were produced by following the same steps as described above by reference to Figs. 2 to 6. The sample which uses a resist film as the organic film 36 was produced by following the same steps as described above by reference to Fig. 2 and Figs. 4 to 6 except the organic film formation step of Fig. 3A. In the case of this sample, the following step was taken for the organic film formation step of Fig. 3A: after rotary coating of a resist film on the upper face of the substrate, the resist film was pre-baked and subjected to exposure and development to form connecting holes 36a to 36c and then the resist film was baked at 250°C to make

it a film suitable for practical use.

Table 2 reveals that cracking occurred only at -40°C or less in the samples using a polyimide film or a resist film as the organic film 36. In addition, in the subsequent step where these samples were heated to 250°C , cracking did not occur. Therefore, the magnetic sensor according to the present invention has an advantage that cracking does not occur in the temperature range from -40°C to 250°C .

For comparison, Table 3 shows the results of cracking temperature measurements formed in the same manner as described above concerning a sample without a substitute film for the organic film 36 and samples with an Au substitute film for the organic film 36.

[Table 3]

Substitute film	Material	None	Au	Au
	Thickness		2 μm	4 μm
Cracking temperature		25 $^{\circ}\text{C}$ or more	0-25 $^{\circ}\text{C}$	0-25 $^{\circ}\text{C}$

In the case of the sample having no substitute film, the organic film 36 was not formed through the step of Fig. 3A and the magnetic shield layer 42 was formed on the insulating film 34 through the steps of Fig. 3B and Fig. 4A. This type of magnetic sensor chip is conventional. In the case of the samples having an Au film, a 2 or 4 μm thick Au film was formed instead of the organic film 36 which would be formed through the step of Fig. 3A and the magnetic shield layer 42 was formed on the Au film through the steps of Fig. 3B and Fig. 4A.

Table 3 shows that cracking is likely to occur in the

sample having no substitute film and that even in the samples having a substitute Au film, cracking occurs in the temperature range from 0 to 25°C. This means that the presence of such Au film does not prevent cracking effectively.

5 After the magnetic sensor chip is fixed to the Cu lead frame 50 through the Ag paste layer 52 as explained above, wires of Au or a similar material are bonded to the bonding pads Pa to Pc. Fig. 19 illustrates how a wire is bonded to a bonding pad (Pb in this example). Here, the same parts or components shown in Fig. 6 are marked with the same reference numerals and symbols. BD represents a bonding wire. The components (magnetoresistive device R_2 , insulating film 34, organic film 36 and so on) lying under the magnetic shield layer 42 are much thinner than the magnetic shield layer 42 and the organic film 44, so they are not shown in this figure.

(Second Embodiment)

10
15
20 Fig. 20 shows a magnetic sensor according to the second embodiment of the present invention. On the insulating surface of the substrate 10, magnetoresistive devices R_{31} and R_{32} having the same structure as the magnetoresistive devices R_1 and R_2 (Fig. 1) are connected in series. Further, magnetoresistive devices R_{33} and R_{34} having the same structure as the magnetoresistive devices R_1 and R_2 are connected in series. R_{32} and R_{33} are covered through the insulating film 34 and the organic film 36 by the magnetic shield layers 42a and 42b, respectively, in the same manner as shown in Fig. 1A. Alternatively, the magnetic shield layers 42a and 42b may be

not separated from each other but constitute a single continuous magnetic shield layer.

5 The serial path of magnetoresistive devices R_{31} and R_{32} and that of magnetoresistive devices R_{33} and R_{34} are connected in parallel. A bonding pad P_{11} is connected at the section of interconnection of the devices R_{31} and R_{33} , and a bonding pad P_{12} is connected at the section of interconnection of the devices R_{32} and R_{34} . Also, a bonding pad P_{13} is connected at the section of interconnection of the devices R_{31} and R_{32} , and a bonding pad P_{14} is connected at the section of interconnection of the devices R_{33} and R_{34} . In this way, the devices R_{31} to R_{34} constitute a resistance bridge circuit. When a given voltage is applied between the bonding pads P_{11} and P_{12} , an output voltage which depends on the external magnetic field is generated between the bonding pads P_{13} and P_{14} .

10
15
20 Like the magnetic sensor shown in Fig. 1A, the magnetic sensor shown in Fig. 20 also prevents cracking in the substrate 10 at the portions covered by the magnetic shield layers 42a and 42b, as described above.

20 A possible variation of the magnetic sensor shown in Fig. 20 is that two magnetic sensors of the same type as the one in Fig. 1A are connected in accordance with the same layout as shown in Fig. 20 to constitute a resistance bridge circuit. This variation will provide the same operation and advantage as the magnetic sensor shown in Fig. 20.

25 Fig. 21 shows an analytic model used for computer simulation called FEM (Finite Element Method) analysis as viewed

from above. Here, a silicon chip 62 which corresponds to the substrate (magnetic sensor chip) 10 is fixed on the surface of a lead frame 60, which corresponds to the Cu lead frame 50. Magnetic shield layers 64 and 66, which correspond to the magnetic shield layer 42 are fixed on the surface of the silicon chip 62 with a given interval between them. The magnetic shield layer 64 and magnetic shield layer 66 as fixed on the silicon chip 62 are identical in structure. Here, the structure of the magnetic shield layer 64 as fixed will be explained below, referring to the sectional view taken along the line XXII-XXII in Fig. 21.

Fig. 22 is a sectional view taken along the line XXII-XXII in Fig. 21 in the case that a thermal stress relief film is used in the magnetic shield layer structure. A silicon oxide film 68 is formed on the surface of the silicon chip 62 and the magnetic shield layer 64 is fixed on the silicon oxide film 68 through the thermal stress relief film 70, which corresponds to the above organic film 36.

The magnetic shield layer 64 is a lamination constituted of a smaller rectangular magnetic shield layer (lower layer) 72 and a larger rectangular magnetic shield layer (upper layer) 74. The magnetic shield layers 72 and 74 are laid one upon the other in a way that an undercut 72a is formed at the bottom of each side wall of the magnetic shield layer 64 where the undercut has a square cross section in the direction of depth along the four sides of the magnetic shield layer 64 (right and left bottom portions shown in the figure). The

magnetic shield layers 72 and 74 are both made of a Ni-Fe alloy with a Ni content of 45%, and have a thickness of 0.8 μm and a thickness of 9.2 μm , respectively.

Fig. 23 shows the result of analysis of the maximum stress generated on the silicon chip 62 with three different thicknesses of the thermal stress relief film 70 (0 μm , 0.5 μm , 1 μm). In this analysis, stress was generated on the surface of the silicon chip 62 by decreasing the temperature from 180°C to -40°C. This temperature condition is the same as used for the stress analysis as described later. Fig. 23 shows that the maximum stress is smaller in the presence of a 0.5 μm or 1 μm thick thermal stress relief film 70 than in the absence of a thermal stress relief film 70 (i.e., 0 μm thickness).

Fig. 24 is a cross sectional view taken along the same line in Fig. 21 concerning the structure of the magnetic shield layer 64 where the above thermal stress relief film 70 does not exist but the magnetic shield layer 64 is made of a Ni-Fe alloy having a low Ni content. In Fig. 24, the same portions as those shown in Figs. 21 and 22 are marked with the same reference numerals and their detailed descriptions are omitted here.

It is known that Ni-Fe alloys with different composition ratios have different expansion coefficients. Figs. 25 and 26 show the results of analysis of maximum stress on the surface of the silicon chip 62 where the Ni content of the Ni-Fe alloy as the material for the magnetic shield layer 64 is changed. Fig. 25 shows that the stress on the silicon chip is the minimum with a Ni content of 36% and the stress is smaller with a Ni

content of 69% or less (preferably from 32% to 50%) than with a Ni content of 70% or more.

Accordingly, in the magnetic shield layer structure as illustrated in Fig. 24, the Ni content of the magnetic shield layer 64 (72, 74) should be 69% or less (preferably from 32% to 50%). The use of such a magnetic shield layer 64 with a low Ni content will lead to reduction in stress due to its lower expansion coefficient, thus preventing cracking in the chip. In the magnetic shield layer structure illustrated in Fig. 22, it is desirable to use a Ni-Fe alloy with a Ni content of 69% or less (preferably from 32% to 50%) to form a magnetic shield layer 64 (72, 74). In addition to the stress reducing effect of the thermal stress relief film 70, the use of such a magnetic shield layer 64 reduces stress because its expansion coefficient is relatively low, so cracking in the chip can be prevented more effectively. In order to obtain a magnetic shield layer 64 of a Ni-Fe alloy with a low Ni content, the ratio of nickel sulfate to iron sulfate should be varied appropriately.

Figs. 27 to 29 are sectional views taken along the same line in Fig. 21 where the profile of the bottom portion of each side wall of the magnetic shield layer is different. In Figs. 27 to 29, the same portions as those shown in Figs. 21 and 22 are marked with the same reference numerals and their detailed descriptions are omitted here.

In the structure illustrated in Fig. 27, there is no undercut at the bottom of each side wall of the magnetic shield layer 64. In other words, the magnetic shield layers 72 and 74

are rectangular and virtually identical in size and each side wall of the magnetic shield layer 64 is upright and straight from the bottom to the top. In the structure illustrated in Fig. 28, there is an undercut 72a with a square cross section along the bottom of each side wall of the magnetic shield layer 64 as stated above by reference to Fig. 22. In the structure illustrated in Fig. 29, there is an undercut 72b along the bottom of each side wall of the magnetic shield layer 64 which is the same as the undercut 72a shown in Fig. 28 except that the undercut 72b has a triangular cross section in the direction of depth (right and left bottom portions shown in Fig. 29).

Fig. 30 shows the maximum stress generated on the surface of the silicon chip 62 concerning the magnetic shield layer structures shown in Figs. 27 to 29. In the graph of Fig. 30, "No undercut," "Undercut A" and "Undercut B" correspond to the structures shown in Figs. 27, 28 and 29, respectively. Fig. 30 shows that the structure with no undercut (Fig. 27) generates less stress than the structures shown in Figs. 28 and 29.

Therefore, when the magnetic shield layer structures as described above by reference to Figs. 22 and 24 have no undercut as shown in Fig. 27, cracking in the chip can be prevented more effectively. In order to obtain a structure with no undercut as shown in Fig. 27, in the coating step as described above by reference to Fig. 4A, the thickness of the resist layer 40 should be increased to prevent the upper portion of the magnetic shield layer 42 from protruding horizontally.

The above embodiments may be implemented in other

specific forms. For instance, a high permeability alloy other than Ni-Fe alloy may be used as the material for the magnetic shield layer and an alloy with a smaller expansion coefficient may be used.

5
As discussed so far, according to the present invention, an organic film for relieving thermal stress is formed under the magnetic shield layer and/or a Ni-Fe alloy having a Ni content of 69% or less is used as the material for the magnetic shield layer in order to prevent cracking in the magnetic sensor chip which has been bonded. As a result, the yield rate in the manufacture of magnetic sensors is improved.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2